GDB QUICK REFERENCE GDB Version 5

Essential Commands

gdb program [core]	debug program [using coredump core]
b [le :]function	set breakpoint at $function$ [in le]
run [arglist]	start your program [with arglist]
bt	backtrace: display program stack
p expr	display the value of an expression
c	continue running your program
n	next line, stepping over function calls
S	next line, stepping into function calls

Starting GDB

gdb	start GDB, with no debugging les
gdb program	begin debugging program
gdb program core	debug coredump <i>core</i> produced by <i>program</i>
gdbhelp	describe command line options

Stopping GDB

quit	exit GDB; als
INTERRUPT	(eg C-c) term
	to running p

so q or EOF (eg C-d) ninate current command, or send process

Getting Help help

Gound Holb	
help	list classes of commands
help class	one-line descriptions for commands in <i>class</i>
help command	describe command

Executing your Program

run <i>arglist</i>	start your program with arglist
run	start your program with current argument list
<pre>run <inf>outf</inf></pre>	start your program with input, output redirected
kill	kill running program
tty dev	use dev as stdin and stdout for next run
set args <i>arglist</i>	specify arglist for next run
set args	specify empty argument list
show args	display argument list
show env	show all environment variables
show env var	show value of environment variable var
set env var string	set environment variable var
unset env var	remove var from environment

Shell Commands

cd dir	change working directory to dir
pwd	Print working directory
make	call "make"
shell cmd	execute arbitrary shell command string

Breakpoints and Watchpoints bre

Dieakpoints an	u watenpoints
break $[le :]line$	set breakpoint at <i>line</i> number [in <i>le</i>]
b $[le :]line$	eg: break main.c:37
break $[le :] func$	set breakpoint at func [in le]
break + $oset$	set break at oset lines from current stop
break - <i>oset</i>	
break $*addr$	set breakpoint at address $a d dr$
break	set breakpoint at next instruction
break if $expr$	break conditionally on nonzero $expr$
cond $n \lfloor expr \rfloor$	new conditional expression on breakpoint n ; make unconditional if no $expr$
tbreak	temporary break; disable when reached
rbreak $regex$	break on all functions matching $regex$
watch $expr$	set a watchpoint for expression $expr$
catch event	break at <i>event</i> , which may be catch , throw , exec , fork , vfork , load , or unload .
info break	show dened breakpoints
info watch	show dened watchpoints
clear	delete breakpoints at next instruction
clear $[le :] fun$	delete breakpoints at entry to $fun()$
clear $[le :]line$	delete breakpoints on source line
delete $[n]$	delete breakpoints [or breakpoint n]
disable $\begin{bmatrix} n \end{bmatrix}$	disable breakpoints [or breakpoint n]
enable $[n]$	enable breakpoints or breakpoint n
enable once $\left[n ight]$	enable breakpoints [or breakpoint n]; disable again when reached
enable del $\left[n ight]$	enable breakpoints [or breakpoint n]; delete when reached
ignore <i>n</i> count	ignore breakpoint $n, \ count \ times$
$egin{array}{c \mbox{ommands} n \ [silent] \ command-list \end{array}$	execute GDB command-list every time breakpoint n is reached. [silent suppresses default display]
end	end of command-list

Program Stack backtr

1

backtrace $\begin{bmatrix} n \end{bmatrix}$	print trace of all frames in stack; or of n
bt $[n]$	frames—innermost if $n>0$, outermost if $n<0$
frame $[n]$	select frame number n or frame at address n ;
	if no n , display current frame
up n	select frame n frames up
down n	select frame n frames down
info frame $\left[a d d r ight]$	describe selected frame, or frame at $addr$
info args	arguments of selected frame
info locals	local variables of selected frame
info reg $[rn]$	register values for regs rn in selected frame;
info all-reg $[rn]$	all-reg includes oating point

Execution Control cont

Execution Control		
continue [count]	continue running; if <i>count</i> specied, ignore	
c [count]	this breakpoint next <i>count</i> times	
step [count] s [count]	execute until another line reached; repeat <i>count</i> times if specied	
stepi [count] si [count]	step by machine instructions rather than source lines	
$\begin{array}{c} \texttt{next} \ [\textit{count}] \\ \texttt{n} \ [\textit{count}] \end{array}$	execute next line, including any function calls	
nexti $[count]$ ni $[count]$	next machine instruction rather than source line	
until $[location]$ finish	run until next instruction (or <i>location</i>) run until selected stack frame returns	
return $[expr]$	pop selected stack frame without executing [setting return value]	
signal <i>num</i>	resume execution with signal s (none if 0)	
jump <i>line</i> jump * <i>address</i>	resume execution at specied <i>line</i> number or <i>address</i>	
set var= $expr$	evaluate <i>expr</i> without displaying it; use for altering program variables	
Display		
Display		
print $\left[/ f \right] \left[expr \right]$	show value of <i>expr</i> [or last value \$] according to format <i>f</i> :	
$\begin{array}{c} \texttt{print} \left[/ f \right] \left[expr \right] \\ \texttt{p} \left[/ f \right] \left[expr \right] \end{array}$	to format <i>f</i> :	
$\begin{array}{c} \texttt{print} \left[/ f \right] \left[expr \right] \\ \texttt{p} \left[/ f \right] \left[expr \right] \\ \texttt{x} \\ \texttt{d} \\ \texttt{u} \end{array}$	to format f: hexadecimal signed decimal unsigned decimal	
print [/f] [expr] p [/f] [expr] x d u o	to format f: hexadecimal signed decimal unsigned decimal octal	
<pre>print [/f] [expr] p [/f] [expr] x d u o t</pre>	to format f: hexadecimal signed decimal unsigned decimal octal binary	
print [/f] [expr] p [/f] [expr] x d u o	to format f: hexadecimal signed decimal unsigned decimal octal binary address, absolute and relative	
<pre>print [/f] [expr] p [/f] [expr] x d u o t a</pre>	to format f: hexadecimal signed decimal unsigned decimal octal binary	
<pre>print [/f] [expr] p [/f] [expr]</pre>	to format f: hexadecimal signed decimal unsigned decimal octal binary address, absolute and relative character	
$\begin{array}{c} \texttt{print} \left[/ f \right] \left[expr \right] \\ \texttt{p} \left[/ f \right] \left[expr \right] \\ \texttt{x} \\ \texttt{d} \\ \texttt{u} \\ \texttt{o} \\ \texttt{t} \\ \texttt{a} \\ \texttt{c} \\ \texttt{f} \\ \texttt{call} \left[/ f \right] expr \\ \texttt{x} \left[/ Nuf \right] expr \end{array}$	to format f: hexadecimal signed decimal unsigned decimal octal binary address, absolute and relative character oating point like print but does not display void examine memory at address <i>expr</i> ; optional format spec follows slash	
<pre>print [/f] [expr] p [/f] [expr] x d u o t a c f call [/f] expr x [/Nuf] expr N</pre>	to format f: hexadecimal signed decimal unsigned decimal octal binary address, absolute and relative character oating point like print but does not display void examine memory at address <i>expr</i> ; optional format spec follows slash count of how many units to display	
$\begin{array}{c} \texttt{print} \left[/ f \right] \left[expr \right] \\ \texttt{p} \left[/ f \right] \left[expr \right] \\ \texttt{x} \\ \texttt{d} \\ \texttt{u} \\ \texttt{o} \\ \texttt{t} \\ \texttt{a} \\ \texttt{c} \\ \texttt{f} \\ \texttt{call} \left[/ f \right] expr \\ \texttt{x} \left[/ Nuf \right] expr \end{array}$	to format f: hexadecimal signed decimal unsigned decimal octal binary address, absolute and relative character oating point like print but does not display void examine memory at address <i>expr</i> ; optional format spec follows slash count of how many units to display unit size; one of	
<pre>print [/f] [expr] p [/f] [expr] x d u o t a c f call [/f] expr x [/Nuf] expr N</pre>	to format f: hexadecimal signed decimal unsigned decimal octal binary address, absolute and relative character oating point like print but does not display void examine memory at address <i>expr</i> ; optional format spec follows slash count of how many units to display unit size; one of b individual bytes	
<pre>print [/f] [expr] p [/f] [expr] x d u o t a c f call [/f] expr x [/Nuf] expr N</pre>	to format f: hexadecimal signed decimal unsigned decimal octal binary address, absolute and relative character oating point like print but does not display void examine memory at address <i>expr</i> ; optional format spec follows slash count of how many units to display unit size; one of b individual bytes h halfwords (two bytes)	
<pre>print [/f] [expr] p [/f] [expr] x d u o t a c f call [/f] expr x [/Nuf] expr N</pre>	to format f: hexadecimal signed decimal unsigned decimal octal binary address, absolute and relative character oating point like print but does not display void examine memory at address <i>expr</i> ; optional format spec follows slash count of how many units to display unit size; one of b individual bytes	
<pre>print [/f] [expr] p [/f] [expr] x d u o t a c f call [/f] expr x [/Nuf] expr N</pre>	to format f: hexadecimal signed decimal unsigned decimal octal binary address, absolute and relative character oating point like print but does not display void examine memory at address <i>expr</i> ; optional format spec follows slash count of how many units to display unit size; one of b individual bytes h halfwords (two bytes) w words (four bytes)	

disassem $\begin{bmatrix} a d d r \end{bmatrix}$

.

Automatic Display

display $\left[/f ight] expr$	show value of $expr$ each time program stops [according to format f]
display	display all enabled expressions on list
undisplay n	remove $number(s)$ <i>n</i> from list of
	automatically displayed expressions
disable disp n	disable display for $expression(s)$ number n
enable disp n	enable display for $expression(s)$ number n
info display	numbered list of display expressions

i machine instructions

display memory as machine instructions

surround optional arguments ... show one or more arguments

Expressions

-
addr©len le ::nm
$\{type\}$ add r
trypefaaar \$
\$n
\$\$
\$\$ <i>n</i>
\$_
\$
\$ v a r

expr

show values $\begin{bmatrix} n \end{bmatrix}$ show conv

Symbol Table info address s

info func [regex]

info var [reg ex]

whatis expr

ptype [expr]

ptype type

define cmd

document cmd

end

end

show where symbol s is stored
show names, types of dened functions (all, or matching $reg ex$)
show names, types of global variables (all, or matching $regex$)
show data type of <i>expr</i> [or \$] without evaluating; ptype gives more detail
describe type, struct, union, or enum

an expression in C, C++, or Modula-2

a variable or function *nm* dened in *le*

read memory at addr as specied type

convenience variable; assign any value

show last 10 values [or surrounding \$n]

an array of *len* elements beginning at *addr*

(including function calls), or:

most recent displayed value

displayed value previous to \$

*n*th displayed value back from \$ last address examined with x

display all convenience variables

nth displayed value

value at address \$_

GDB Scripts source *script*

rce <i>script</i>	read, execute GDB commands from le $\ script$
ine cmd command-list	create new GDB command <i>cmd</i> ; execute script dened by <i>command-list</i> end of <i>command-list</i>
ument cmd help-text	create online documentation for new GDB command <i>cmd</i> end of <i>help-text</i>

Signals

handle signal act	specify GDB actions for <i>signal</i> :
print	announce signal
noprint	be silent for signal
stop	halt execution on signal
nostop	do not halt execution
pass	allow your program to handle signal
nopass	do not allow your program to see signal
info signals	show table of signals, GDB action for each

Debugging Targets

connect to target machine, process, or le
display available targets
connect to another process
release target from GDB control

Controlling GDB

Controlling GDB		
set param value	set one of GDB's internal parameters	
show $param$	display current setting of parameter	
Parameters understoo	od by set and show:	
complaint <i>limit</i>	number of messages on unusual symbols	
confirm on/o	enable or disable cautionary queries	
editing on/o	control readline command-line editing	
height lpp	number of lines before pause in display	
language lang	Language for GDB expressions (auto, c or modula-2)	
listsize n	number of lines shown by list	
prompt str	use str as GDB prompt	
radix base	octal, decimal, or hex number representation	
verbose $\mathit{on/o}$	control messages when loading symbols	
width cpl	number of characters before line folded	
write on/o	Allow or forbid patching binary, core les (when reopened with exec or core)	
history	groups with the following options:	
h		
h exp o/on	disable/enable readline history expansion	
h file lename	le for recording GDB command history	
h size <i>size</i>	number of commands kept in history list	
h save o/on	control use of external le for command history	
print	groups with the following options:	
р		
p address $\mathit{on/o}$	print memory addresses in stacks, values	
p array o/on	compact or attractive format for arrays	
p demangl on/o	source (demangled) or internal form for C++ symbols	
p asm-dem on/o	demangle C++ symbols in machine- instruction output	
p elements $limit$	number of array elements to display	
p object $\mathit{on/o}$	print C++ derived types for objects	
p pretty o/on	struct display: compact or indented	
p union on/o	display of union members	
p vtbl o/on	display of C++ virtual function tables	
show commands	show last 10 commands	
show commands n	show 10 commands around number n	
show commands +	show next 10 commands	

Working Files

file $\begin{bmatrix} le \end{bmatrix}$	use <i>le</i> for both symbols and executable; with no arg, discard both
$ ext{core} egin{bmatrix} le \ \end{bmatrix} \\ ext{exec} egin{bmatrix} le \ \end{bmatrix} \end{bmatrix}$	read <i>le</i> as coredump; or discard
exec $\begin{bmatrix} le \end{bmatrix}$	use le as executable only; or discard
symbol $[le]$	use symbol table from le ; or discard
load le	dynamically link <i>le</i> and add its symbols
$add-sym \ le \ addr$	read additional symbols from le , dynamically loaded at $addr$
info files	display working les and targets in use
path dirs	add <i>dirs</i> to front of path searched for executable and symbol les
show path	display executable and symbol le path
info share	list names of shared libraries currently loaded

F:1 \mathbf{S}

Source Files	
dir <i>names</i>	add directory names to front of source path
dir	clear source path
show dir	show current source path
list	show next ten lines of source
list -	show previous ten lines
list $lines$	display source surrounding <i>lines</i> , specied as:
[le :]num	line number [in named le]
[le :] function	beginning of function $\begin{bmatrix} in named le \end{bmatrix}$
+ 0	o lines after last printed
- 0	o lines previous to last printed
* a d dress	line containing $address$
list f, l	from line f to line l
info line num	show starting, ending addresses of compiled code for source line <i>num</i>
info source	show name of current source le
info sources	list all source les in use
forw $regex$	search following source lines for <i>regex</i>
rev $regex$	search preceding source lines for $regex$

GDB under GNU Emacs

M-x gdb	<pre>run GDB under Emacs</pre>
C-h m	describe GDB mode
M-s	step one line (step)
M-n	next line (next)
M-i	step one instruction (stepi)
C-c C-f	nish current stack frame (finish)
M-c	continue (cont)
М-с	continue (cont)
М-ц	up arg frames (up)
М-d	down arg frames (down)
С-х &	copy number from point, insert at end
С-х SPC	(in source le) set break at point

GDB License

show copying	Display GNU General Public License
show warranty	There is NO WARRANTY for GDB. Display
	full no-warranty statement.

Copyright c 1991,'92,'93,'98,2000 Free Software Foundation, Inc. Author: Roland H. Pesch

The author assumes no responsibility for any errors on this card.

This card may be freely distributed under the terms of the GNU General Public License.

Please contribute to development of this card by annotating it. Improvements can be sent to bug-gdb@gnu.org.

GDB itself is free software; you are welcome to distribute copies of it under the terms of the GNU General Public License. There is absolutely no warranty for GDB.